



Blackmagic Design GPI and Tally Interface

Description

Add tally to your ATEM switcher with Blackmagic Design's GPI and Tally Interface! With 8 contact closure tally outputs, you can send a tally signal to your cameras, replay machines and monitors so everyone knows which camera is 'on-air'! If you need more tally outputs, simply connect multiple GPI and Tally Interfaces together because it connects via Ethernet to your ATEM production switcher.

Connections

Contact Closure

25 pin D-type connector providing 8 opto isolated inputs and 8 relay contact closure outputs.

Inputs

Optical isolators triggered by connection to ground. Max 5V at 14mA.

Outputs

Mechanical relay contact closure to ground. Max 30V at 1A.

Ethernet

10/100 BaseT with loop through for connecting to other ethernet enabled equipment.

Computer Interface

1 x USB 2.0 high speed interface for configuration and firmware updates.



Software Included

Configured via ATEM Switcher Utility.