

The ALB229 Series 300W Ku-Band BUC is ideal for mobile and satellite uplink applications.

The BUC has "Best in Class" efficiency and "lowest power consumption." The unit works on a wide range AC power supply of 96VAC to 264VAC.

Built-in redundancy feature eliminates the use of an external controller for 1:1 redundancy operation. This eliminates messy cabling at the antenna making this a very elegant solution.

Extensive M/C interface with RS232/RS485/ and Ethernet (SNMP & HTTP).

Features

- · Available in standard and extended Ku-Band
- Forward & reverse power detection
- · Input power detection
- Intuitive monitoring & control through RS232/RS485 & Ethernet (SNMP & HTTP)
- · Automatic fault identification & alarm generation
- Temperature compensation facility
- Built-in redundancy facility
- Built-in 10MHz reference with auto-detection
- Built-in receive reject filter
- · Sample port for output monitoring
- Wide operating temperature range 0°C to +50°C
- RoHS Compliant

Quality Assurance

100% of all BUCs go through stringent quality checks in addition to well defined Electrical Stress Screening to ensure operation.

Reliability

Field proven under harsh environment conditions, Agilis IDUs can withstand temperature ranging from -0°C to +50°C with up to 95% humidity.



ALB229 Series

300W Ku-Band Block-Up Converter

Technical Specifications

RF Specifications

 Transmit Frequency
 14.0GHz - 14.5GHz

 13.75GHz - 14.5GHz

 IF Frequency Range
 950MHz - 1450MHz

 950MHz - 1700MHz

LO Frequency 13.05GHz 12.80GHz

Output Power (Psat)

Spectral Re-growth 30dBc @ PLinear

Third Order Intermod (two tone) -25dBc @ Relative to combine power of two

55dRm

carrier at 3dB total power backoff from

PLinea

Small Signal Gain

 300W
 80dB Min

 Gain Flatness Full Band
 ±2dB

 Gain Slope over 40MHz
 ±1dB

Gain Variation over temperature ±1dB @ from -0°C to +50°C
Gain Control 20dB in step of 0.5dB

O/P spurious According to EN301428

Phase Noise @ Offset

 1KHz
 -75dBc/Hz

 10KHz
 -85dBc/Hz

 100KHz
 -95dBc/Hz

 I/P VSWR
 1.3:1

 O/P VSWR
 1.25:1

 Noise Power Density Tx BD
 70dBW/4KHz

Rx BD 142dBW/4KHz

Maximum Input Power +10 dBm (without damage)

Noise Figure at Gain max Display

10.0 dB max 24 x 2 LCD Display

Power Supply 220 Vac, 1 phase ±10.0%

Frequency Voltage 47Hz ~ 63Hz

Power

Prime Power 230VAC (range 96V to 264VAC)

Power Consumption 2.5 KW

Interfaces

IF Input Interface 50Ohms N-type Female

Output Interface WR 75G

External Reference

 Frequency
 10MHz

 Power
 -5dBm to +5dBm

 Internal reference
 Built-in (Auto detection)

External reference phase noise Requirement @ frequency offset

 1KHz
 -150dBc/Hz

 10KHz
 -155dBc/Hz

 100KHz
 -160dBc/Hz

Monitor And Control

Monitor BUC temperature

Status alarm Output power Reverse power Input power LED status indication

Control Attenuation
RF output mute

Interface RS485 & Ethernet (SNMP & HTTP)

Tx Redundancy Built-in

Environmental

Operating Temperature -0°C to +50°C

Humidity Up to 100%

Weather protection sealed to IP65

Mechanical

Color

Size 19" rack, 7RU height

Weight 50kg

Compliance Standard

IEC 609501-2nd Edition International Safety Standard for Information

Grey

Technology Equipment

ETSI EN 301 489-12 Electromagnetic Compatibility and Radio Spectrum

Matters (ERM); ElectroMagnetic Compatibility (EMC) Standard for radio equipment and services; Part 12: Specific conditions for Very Small Aperture Terminal, Satellite Interactive Earth Stations operated in the frequency ranges between 4GHz and 30GHz in the

Fixed Satellite Service (FSS)

ETSI EN 301 489-1 Electromagnetic Compatibility and Radio

Spectrum Matters (ERM); ElectroMagnetic

Compatibility Standard for Radio Equipment and Services

FCC Class A Two levels of radiation and

conducted emissions Limits for unintentional radiators (FCC Mark)

Note: All specifications are subject to change without notice. Rev. 031013

www.agilissatcom.com

For more information, please send enquiry to:

Singapore (Headquarters)
mktg_satcoms@stee.stengg.com

USA

usa satcoms@stee.stengg.com

Europe

europe satcoms@stee.stengg.com

